

JCB ENERGY ELECTRIC POWER INDUSTRY











IVECO

















231 / 400 V - 50 Hz & 277 / 480 V - 60 Hz





GENERATOR GENERAL INFORMATION

GENERATOR	FREQUENCY	VOLTAGE	POWER FACTOR	SPEED	DIESEL	ENGINE		ALTERN	ATOR		TYPE OF	GENEF	RATOR O	UTPUT
Model	Hz	V	Cos Q	Rpm	Brand	Model	Series	Brand	Model	Series	Operation	kVA	kW	Α
						JCN E32C	E32C EII	JCBENERG)	JCB	180M	Standby	26,0	20,8	37,6
JCN 26	50	231/400	0.8	1500							Prime	23,6	18,9	34,2
					ICNI						Continuous	16,5	13,2	23,9
					JCN						Standby	31,0	24,8	44,8
JCN 31	60	277/480	0.8	1800							Prime	28,2	22,5	40,7
									,		Continuous	19,7	15,8	28,5

- Diesel Engines with Advanced Technology and Quality
- Alternators with Advanced Technology and Quality
- Low Exhaust Emission
- Control Panel Suitable for Flexible Application
- Patented Compact Designed and Sound proof Canopy
- Low Operating Cost, Suitable for Heavy-Duty
- Durability, Low Noise Level

- Tropical 50 °C Radiator, First Class Product Support
- Fuel Filter with Water and Particle Separator
- Low Fuel Consumption, Low Oil Consumption
- Global Technical Service and Maintenance Support
- Wide Range of Affordable Spare Parts
- High Quality and Reliable Technology
- Half Century Experience in Generator Manufacturing

STAND BY POWER RATING - (ESP):

ESP is applicable for supplying emergency power for the duration of the utility power outage. No overload capability is available for this rating. Under no condition is an engine allowed to operate in parallel with the public utility at the Stand by Power rating. This rating should be applied where reliable utility power is available. A Stand By rated engine should be sized for a maximum of an 70% average load factor and 200 hours of operation per year. This includes less than 25 hours per year at the Stand by Power rating. Stand By ratings should never be applied except in true emergency power outages. Negotiated power outages contracted with a utility company are not considered an emergency.

PRIME POWER RATING - (PRP):

Applicable for supplying electric power in lieu of commercially purchased power. Prime Power applications must be in the form of one of the following two categories:

UNLIMITED TIME RUNNING PRIME POWER (ULTP):

PRP (Prime Power) is available for an unlimited number of hours per year in a variable load application. Variable load should not exceed a 70% average of the Prime Power rating during any operating period of 250 hours. The total operating time at 100% Prime Power shall not exceed 500 hours per year. A 10% overload capability is available for a period of 1 hour within a 12-hour period of operation. Total operating time at the 10% overload power shall not exceed 25 hours per year.

LIMITED TIME RUNNING PRIME POWER (LTP):

LTP (Limited Time Prime Power) is available for a limited number of hours in a no variable load application. It is intended for use in situations where power outages are contracted, such as in utility power curtailment. Engines may be operated in parallel to the public utility up to 750 hours per year at power levels never to exceed the Prime Power rating. The customer should be aware, however, that the life of any engine will be reduced by this constant high load operation. Any operation

CONTINUOUS POWER RATING (COP):

COP is the power that the engine can continue to use under the prescribed speed and the specified environment condition in the normal maintenance period stipulated in the manufacturing plant. And Continuous Power is applicable for supplying utility power at a constant 100% load for an unlimited number of hours per year. No overload capability is available for this rating.



231 / 400 V - 50 Hz & 277 / 480 V - 60 Hz



PAY ATTENTION TO THE POINTS BELOW IN PICKING AND USING THE GENERATOR

- * Generators can work on Continuous Power at 70% of Prime power value if only all maintenances are done on time with original spare parts and high-quality oils that manufacturer advice.
- * Generators should not operate below 50% of Prime Power value. In such a case, the engine will burn excessive oil and eventually have irreparable damage.
- * If your need is 1000 kVA or above, you should prefer Synchronic Systems with 2-3 generators with failure back up and simultaneous aging.
- * These points will provide advantage for you with purchasing and operating the generator.

GENERATOR DIMENSIONS AND TECHNICAL DRAWINGS






VALUES		OPEN TYPE GENERATOR	CANOPY TYPE GENERATOR
WIDTH	mm	597	1000
LENGTH	mm	1400	2000
HEIGHT	mm	1309	1444
WEIGHT (NET)	Kg	553	690
FUEL TANK CAPACITY	L	58	100


SYMBOL	OPEN	CANOPY	
L	1400	2000	
W	597	1000	
Н	1004	1240	
S	360	90	
Α	555		
В	500		
С	480		
D1		800	
D2		800	
D3		400	
D4			
D5			











FUEL CONSUMPTION

PERCENT OF PRIME POWER	1500 rpm	1800 rpm
TENGENT OF THIME FOREIG	l/hr	I/hr
110 %	6,17	7,40
100 %	5,60	6,74
75 %	4,30	5,18
50 %	3,07	3,70



231 / 400 V – 50 Hz & 277 / 480 V – 60 Hz



DIESEL ENGINE MAIN TECHNICAL PARAMETERS

GENERAL		
Number of Cylinders		4
•		
Configuration		Vertical, In Line
Aspiration		Naturally
Combustion System		Direct Injection
Compression Ratio		19.1:1
Bore	mm	93
Stroke	mm	102
Displacement	L	2,27
Governing Type		Mechanic
Governing Class		G2
Rotation		Counterclockwise
Firing Order		1-3-4-2
Emission		Tier II
Moments of Rotation Inertia		
Engine	Kg - m²	0,44
Flywheel	Kg - m ²	2,55
Performance Rating	Kg - III	2,33
Speed Droop	%	≤3
Steady State Speed Band	%	≤0,5
FILTERS		Dry Type Benjaceable
Air Filter		Dry Type, Replaceable
Fuel Filter		With Water Separator
Oil Filter		Element Type, Particulate Trap
FLYWHEEL HOUSING AND FLEX COUPLING		
Flywheel Housing	SAE (J620)	4
Flex Coupling Disc	Inch (")	7,5
TEST CONDITIONS		
Ambient Temperature	%	25
Atmospheric Pressure	КРа	100
Relative Humidity	Rh (%)	30
Max. Operating Intake Resistance	КРа	5
Exhaust Backpressure Limit	КРа	5
Fuel Temperature (Fuel Inlet Pump)	°C	38±2
OVERALL DIMENSIONS		
Length*	mm	1078
Width Height	mm mm	572 749
Dry Weight	kg	275
*From front end of radiator to near end of air filter	0	
FAN		
Diameter	mm	400
Drive Ratio		1,25:1
Number of Blades		8
Material Type		Plastic Blowing



231 / 400 V – 50 Hz & 277 / 480 V – 60 Hz



DIESEL ENGINE MAIN TECHNICAL PARAMETERS

COOLING SYSTEM			
	5000	Transland	
Radiator Type	50ºC	Tropical	
Total Coolant Capacity	L	13	
Max. Perm. Coolant Outlet Temperature	ōС	103	
Max. Perm. Flow Resist. (Cool. System And Piping)	bar	0,5	
Max. Temperature of Coolant Warning	ōC	95	
Max. Temperature of Coolant Shutdown	ōC	98	
Thermostat Operation Temperature - Initial Open	ōC	68	
Thermostat Operation Temperature - Full Open	ōC	72	
Delivery of Coolant Pump	m^3/h	1,60	
Min. Pressure Before Coolant Pump	bar	0,15	
Radiator Face Area	m²	0,26	
Rows	Row	2	
Matrix Density	Per / Inch	15,5	
Material		Aluminum	
Width of Matrix	mm	440	
Height of Matrix	mm	590	
Pressure Cap Setting	kPa	90	
Estimated Cooling Air Flow Reserve	kPa	0,125	
Engine Pre Heater-Tube (with Circulation Pump)	W	1500	
LUBRICATION SYSTEM			
Total System	L	8	
Minimum Oil Level	L	7	
Nominal Motor Operating Temperature	ōC	40	
Lubricating Oil Pressure (Rated Speed)	bar	5	
Relief Valve Opens	kPa	352	
Oil / Fuel Consumption Ratio	%	≤ 0,3	
Normal Oil Temperature	ōС	110	
ELECTRICAL SYSTEM			
Voltage	V	12	
Starter	kW	3,2	
Alternator Output Ampers	А	25	
Alternator Output Voltage	V	14	
Batteries Capacity	Ah	55	



231 / 400 V – 50 Hz & 277 / 480 V – 60 Hz



JCB ENERGY DIESEL ENGINE POWER RATINGS

ENGINE MODEL	E32C		ENGINE FAMILY JC31		ENGINE SERIES	EII	
		TYPICAL GENERATOR OUTPUT (NET)		ENGINE POWER			
Speed (Rpm)	Type of Operation			Gro	SS	Net	
		kVA	kWe	KWm	Нр	kWm	Нр
1500	Stand By(Maximum)	25,8	20,6	26,0	34,9	24,0	32,2
	Prime	23,8	19,0	23,6	31,7	22,1	29,7
1800	Stand By(Maximum)	30,7	24,6	31,2	41,9	28,9	38,8
	Prime	28,2	22,6	28,4	38,1	26,6	35,7

DIESEL ENGINE MATCHING PARAMETERS - 50 HZ

50 HZ @ 1500 R/MIN		STAND BY	PRIME
Gross Engine Power	kW	26.0	23.6
Net Engine Power	kW	24,0	22,1
Fan Power Consumption (Belt Pulley Driven)	kW	1,5	1,5
Other Power Loss	kW	0,5	0,0
Mean Effective Pressure	MPa	0,92	0,83
Intake Air Flow	m³/min	1,25	1,25
Exhaust Temperature Limit	ōС	300	300
Exhaust Flow	m ³/ min	1,30	1,15
Boost Pressure Ratio		4,10	3,70
Mean Piston Speed	m / s	5,0	5,0
Cooling Fan Air Flow	m ³/ min	46,6	46,6
Typical Generator Output Power	kVA	26	24
HEAT REJECTION		STAND BY	PRIME
Energy in Fuel (Heat of Combustion)	kW	72,7	56,5
Gross Heat to Power	kW	26,0	23,6
Energy to Coolant and Lubricating Oil	kW	26,2	16,1
Heat Dissipation Capacity *	kW	-	-
Energy to Exhaust	kW	16,0	13,1
Heat to Radiation	kW	4,5	3,7

^{*}Intake Intercooled system



231 / 400 V - 50 Hz & 277 / 480 V - 60 Hz



DIESEL ENGINE MATCHING PARAMETERS - 60 HZ

60 HZ @ 1800 R/MIN		STAND BY	PRIME
Gross Engine Power	kW	31,2	28,4
Net Engine Power	kW	28,9	26,6
Fan Power Consumption (Belt Pulley Driven)	kW	1,8	1,8
Other Power Loss	kW	0,5	0,0
Mean Effective Pressure	MPa	0,92	0,83
Intake Air Flow	m³/min	1,50	1,50
Exhaust Temperature Limit	ōС	360	360
Exhaust Flow	m³/min	1,57	1,38
Boost Pressure Ratio		4,90	4,50
Mean Piston Speed	m / s	6,0	6,0
Cooling Fan Air Flow	m³/min	55,9	55,9
Typical Generator Output Power	kVA	31	28
HEAT REJECTION		STAND BY	PRIME
Energy in Fuel (Heat of Combustion)	kW	86,8	66,1
Gross Heat to Power	kW	31,2	26,6
Energy to Coolant and Lubricating Oil	kW	31,4	19,3
Heat Dissipation Capacity *	kW	-	-
Energy to Exhaust	kW	19,2	15,7
Heat to Radiation	kW	4,9	4,5

^{*}Intake Intercooled system

JCB ALTERNATOR TECHNICAL PARAMETERS AND SPECIFICATIONS



ALTERNATOR TECHNIC	CAL PARAMETERS				
Insulation Class		Н	Field Control System		Self-Excited
Winding Pitch		2/3 - (N° 6)	A.V.R. Model	Standard	SX460
Wires		12	Voltage Regulation	%	± 1
Protection		IP 23	Sustained Short-Circuit Current	10 sec	300% (3 IN)
Altitude	m	1000	Total Harmonic (*) TGH / THC	%	< 5
Overspeed	rpm	2250	Wave Form: NEMA = TIF - (*)		< 50
Air Flow	m³/sec.	0.095	Wave Form: I.E.C. = THF - (*)	%	< 2
Bearing Drive	N/A	-	Bearing Non-Drive	Bearing	6306-2RZ
Rotor Winding	100%	Copper	Stator Winding	100%	Copper



231 / 400 V – 50 Hz & 277 / 480 V – 60 Hz



ALTERNATOR SPECIFICATIONS

50 HZ / 231-400V COS	Q 0,8 / 1500 RPM								
STANDARD USING ALTERNATOR				OPTIONAL USING ALTERNATOR					
BRAND/MODEL	JCBENERGY	JCB 180M		LEROY-SO	OMER [™]	TAL042A	STAMFORD	SOL2N	Л
DUTY				Continuous				Stand By	
AMBIENT	C°			40°C				27°C	
CLASS / TEMP. RISE	C°			H/ 125° K				H/ 163° K	
SERIES STAR	V	380/220	400/231	415/240	1 Phase	380/220	400/231	415/240	1 Phase
PARALLEL STAR	V	190/110	200/115	208/120	220	190/110	200/115	208/120	220
SERIES DELTA	V	220	230	240	230	220	230	240	230
OUTPUT POWER	kVA	24,0	24,0	25,0	16,0	26,0	26,0	28,0	18,0
OUTPUT POWER	kW	19,2	19,2	20,0	12,8	20,8	20,8	22,4	14,4

60 HZ / 277-480V COSQ	0,8 / 1800 RPM								
STANDARD USING ALTERNATOR				OPTIONAL U	JSING ALTE	ERNATOR			
BRAND/MODEL	JCBENERGY	JCB 180M		LEROY-S	OMER [®] T	AL042A	STAMFO	ORD	P1144E- S0L2-M
DUTY				Continuous				Stand By	
AMBIENT	C°			40°C				27°C	
CLASS / TEMP. RISE	C°			H / 125° K				H / 163° K	
SERIES STAR	V	416/240	440/254	480/277	1 Phase	416/240	440/254	480/277	1 Phase
PARALLEL STAR	V	208/120	220/127	240/138	-	208/120	220/127	240/138	-
SERIES DELTA	V	240	254	277	240	240	254	277	240
OUTPUT POWER	kVA	28,0	30,0	30,0	20,0	31,0	33,0	33,0	22,0
OUTPUT POWER	kW	22,4	24,0	24,0	16,0	24,8	26,4	26,4	17,6



231 / 400 V - 50 Hz & 277 / 480 V - 60 Hz



CONTROL MODULE ALERTS

Emergency Stop Malfunction
High Generator Frequency
Low Generator frequency, Low Load
Over Current, Unbalanced Current
Low Generator Voltage
High generator Frequency
Phase sequence error
Overload, Heat Sensor Broken
Low Water Level (Optional)
Low Oil Pressure, Reverse Power

Start Error, Stop Error
Magnetic Pickup Error
Charge Alternator Error
Unbalanced Load
Maintenance Time Alarm
Low Speed, High Speed
Broken Oil Sensor Cable
High Oil Temperature (Optional)
Low Fuel Level (Optional), High Battery Voltage
Low Battery Voltage, High Water Temperature
Electronic Can bus Errors (ECU)

CONTROL PANEL SPECIFICATIONS



Low Water Temperature



- Powder Painted Steel Panel with Lockable Door
- ATS (Automatic Transfer Panel) Optional
- Control Module
- Battery Charger
- Emergency Stop Button

- Terminal Blocks
- Load Output Terminal
- System Protection MSBs
- Circuit Breaker-Optional
- LCD Screen
- Control Relays
- Backlit, 128x64 Pixels

CONTROL MODULE TECHNICAL PARAMETERS

Brand	JCBENERGY [*]	Brand	Trans-MIDIAMF.232.GP
Dimensions	120mmx94mm.	Protection Class	IP65 From the Front
Weight	260 gr.	Environmental Conditions 2000 meters above sea level	
Ambient Humidity	Max. %90.	Ambient Temperature -20°C to +70°C	
DC Battery Supply Voltage	8 - 32 V	Battery Voltage Measurement 8 – 32 V	
Network Frequency	5 - 99,9 Hz	Mains Voltage Measurement	3 - 300 V phase -Neutral, 5 - 99,9 Hz
Generator Voltage Measurement	3 - 300 V	Generator Frequency	5 - 99,9 Hz
Current Transformer Secondary	5A	Working Period	Continuous
Charge Alternator Voltage Measurement	8 - 32 V	Charge Alternator Excitation 210mA &12V, 105mA &24V Nomin 2.5W	
Communication Interface	RS-232	Analog Sender Measurement	0 - 1300ohm
Generator Contactor Relay Output	5A & 250V	Mains Contactor Relay Output	5A & 250V
Solenoid Transistor Outputs	1A with DC Supply	Start Transistor Outputs	1A with DC Supply
Configurable-3 Transistor Outputs	1A with DC Supply	Configurable-4 Transistor Outputs	1A with DC Supply



231 / 400 V - 50 Hz & 277 / 480 V - 60 Hz



CONTROL MODULE FUNCTION

Mains Voltage Level Control	Generator Voltage Level Control	3 Phase Generator Protections	3 Phase AMF Function	Alarm Horn
Network Frequency Level Control	Generator Frequency level Control	- High / Low Voltage	- High / Low Frequency	Heater Tube Thermostat Control
Engine Operating Option Control	Generator Current Level Control	- High / Low Frequency	- High / Low Voltage	Modbus and SNMP
Engine Stop Option Control	Generator Powder Level Control	- Current / Voltage Asymmetry	- High / Low Water Temperature	Working Hour
Engine Speed (RPM) Level Control	Generator work Schedule and Timing Control	- Overcurrent / Overload	- High / Low Load	Ground Leakage
Battery Voltage Options Times	Oil Pressure Controllers Control	Overheat Control	Mains., Generator ATS Control	Analog Modem
Check Engine Maintenance Times	Configurable Analog Inputs and Outputs	1 Phase or 3 Phase, Phase Selection	Network, Voltage, Frequency Display	Ethernet, USB, RS232, RS485
Communication Interfaces GPRS, GSM	Keeping Error Records of Past Events	Parameter Setting via Control Module	Parameter Setting via Computer	Selectable Protection Alarm / Shutdown
Engine Speed, Voltage, Earning	Configurable Programmable Digital Inputs and Outputs	Water Temperature Current and Frequency	Hours of Operation Phase sequence	Battery Voltage Oil Pressure

SOUND PROOF CANOPY AND BASE FRAME (CHASIS) SPECIFICATIONS



- Special, Registered JCB Energy Design and Colour
- A1 Quality DKP / HRU / Galvanized Steel
- Sensitive Twist on Automatic Press Brake
- Delicate Cut on Automatic Punch and Laser Bench
- Sensitive Welding on Robotic Welding Bench
- Chemical Cleaning Nano Technology Before Painting
- Robotic Painting with Electrostatic Powder Paint
- O Drying and stabilizing on 200 °C Ovens
- 1500 Hour Salt Test
- o Glass wool Isolation, A1 Class Material -50/+500 ºC
- Special Covering Over Glass Wool
- Best Sound Level (in Dba)
- Temperature Tests
- Rustproof Accessories

- Cable Exit Connectors and Glands
- Emergency Stop Button
- Fuel Level Gauge
- Fuel Drain Cap
- Fuel Inlet and Return Records
- I permeability Test for Fuel Tank
- Vacuumed Rubber Mounted
- High Quality weatherstrips
- High Quality Shock Absorbers
- Fuel Filling Cap (with ventilation)
- Lifting and Carrying Equipment
- Internal Exhaust Mufflers (Silencers)
- External Exhaust Mufflers (Silencers)
- Radiator water Filling Cap
- Daily Fuel Tank, External Fuel Tank

Our Quality Certificates

