

## **FEATURES & ADVANTAGES**

- Simple design
- Large fuel tank capacity for longer running time
- Lower cost
- Stable output
- Low oil auto shutdown



GENERATOR		
Model		JPG 5500
Rated Output	KW	5.0/5.5
Max. Output	KW	5.5/6.0
Rated Voltage	V	230/120/240
Frequency	Hz	50/60
Phase Number		Single Phase
Voltage Regulating Type		AVR
Starting System	dBA	Manuel/Electric
<b>Fuel Tank Capacity</b>	L	40
Fuel Consumptions ratio	L/H	2,65
Continuous running time	h	15
Noice dB(A) 25%@ 7m		94/96
Net weight KG		96
Package Dimensions	mm	730/556/660
Engine		JC390
Displacement	ml	389
Oil Capacity	L	1.1
Loading	20GP/40GP/40HQ	93/192/255

