



INVERTER PORTABLE GENERATOR



www.jcbenergy.es

INVERTER PORTABLE GENERATORS

| GROUP | | JP 3300i | JPO 5500i | JP 9000i |
|---------------------------|--------------------|--------------|--------------|----------------|
| Current | A | 13/25/30 | 21,7/20,8 | 32,6/62,5/31,3 |
| Rated Output | KW | 3,0 | 5,0 | 7,5 |
| Max. Output | KW | 3,3 | 5,5 | 9 |
| Rated Voltage | V | 230/120/100 | 230/120 | 230/120/240 |
| Frequency | Hz | 50/60 | 50/60 | 50/60 |
| Phase Number | | Single Phase | Single Phase | Single Phase |
| DC Voltage | V | 12 | 12 | 12 |
| DC Current | A | 8.3 | 8.3 | 8.3 |
| Fuel Tank Capacity | L | 3,7 | 16 | 3,7 |
| Continuous time | (%50 load) | 4 | 9 | 10,5 |
| Net weight KG | | 21,5 | 44 | 110 |
| Engine | | JC164P | JC180P | JC460P |
| Displacement | ml | 145 | 312 | 459 |
| Pack Dimension | mm | 510/230/475 | 685/515/480 | 820/640/780 |
| Loading | 20GP/40GP/ 40HQ | 308/644/805 | 132/272/340 | 74/149/150 |



www.jcbenergy.es