



# GASOLINE PORTABLE GENERATORS

## JPG SERIES



[www.jcbenergy.es](http://www.jcbenergy.es)

# GASOLINE PORTABLE GENERATORS -- JPG SERIES

GROUP		JPG 3000	JPG 5500	JPG 7500	JPG 13000E
<b>Rated Output</b>	KW	2.7/3	5.0/5.5	7.0/7.5	10,0
<b>Max. Output</b>	KW	3/3.2	5.5/6.0	7.5/8.5	11,2
<b>Rated Voltage</b>	V	230/120/240	230/120/240	230/120/240	230
<b>Frequency</b>	Hz	50/60	50/60	50/60	50
<b>Phase Number</b>		Single Phase	Single Phase	Single Phase	Single Phase
<b>Voltage Regulating Type</b>		AVR	AVR	AVR	AVR
<b>Starting System</b>	dBA	Manuel/ Electric	Manuel /Electric	Manuel /Electric	Electric
<b>Fuel Tank Capacity</b>	L	15	40	40	41
<b>Fuel</b>					
<b>Consumptions ratio</b>	L/H	1.45	2,65	3.6	5.8
<b>Continuous running time</b>	h	8	15	11	7
<b>Noice dB(A) 25%@ 7m</b>		92/94	94/96	96/97	98
<b>Net weight KG</b>		52	96	96	142
<b>Package Dimensions</b>	mm	610/460/480	730/556/660	730/556/660	770/630/887
<b>Engine</b>		JC225	JC390	JC460	J670C
<b>Displacement</b>	ml	223	389	458	670
<b>Oil Capacity</b>	L	0,6	1.1	1.1	1.1
<b>Loading</b>	20GP/40GP/ 40HQ	180/380/475	93/192/255	93/192/255	54/108/108



[www.jcbenergy.es](http://www.jcbenergy.es)